

24 Dec. 99

375/1298, 300
(145) 168, 269
1416
375/224, 227
375/285 07/25/01

136

applied 22 Dec 2000

09/890 441

CLAIMS

1. A wander generator comprising: 375/145

random number generating means for sequentially
generating a random number signal comprised of a
5 plurality of bits at a constant rate in accordance with
a predetermined algorithm;

a filter unit for receiving a sequence of random
number signals output from said random number
generating means for performing filtering;

10 clock generating means for generating a clock
signal;

modulating means for modulating the frequency of
the clock signal generated by said clock signal
generator by a signal output from said filter unit; and

15 setting means for setting each amplitude value for
a spectrum of a signal sequence output from said filter
unit such that the characteristic of wander of the
clock signal having the frequency modulated by said
modulating means matches a desired characteristic.

20 2. A wander generator according to claim 1,
characterized in that said random signal generating
means has a plurality of pseudo random signal generator,
wherein said plurality of pseudo random signal
generators combine pseudo random signals generated
25 thereby respectively, and is configured to sequentially
generate random number signals comprised of the
plurality of bits at a constant speed.

09890441-072501

for each of the paths; and

combining means for combining the signal sequences on the respective paths weighted by said weighting means by means of a plurality of sub-band combiners
 5 comprised of a plurality of storage elements and calculating means and for outputting the result of the combination as the result of filtering, and

said setting means sets the plurality of weighting coefficients in said weighting means of said filter
 10 unit as signals for setting respective amplitude values for spectra of the signal sequence output from said filter unit.

6. A wander generator according to claim 3 or 5,
 characterized by further comprising initial setting
 15 means for initially setting values equivalent to stored values stored in said respective storage elements in (a) steady state in which the clock signal having the wander of the desired characteristic is being output to said respective storage elements included in the filter
 20 unit at least in an initial phase of operation of said apparatus through a path different from a signal input path in the steady state.

7. A wander generator according to claim 1,
 characterized by further comprising:

25 characteristic calculating means for calculating a characteristic of wander in a clock signal frequency-modulated by said modulating means based on information

000044-072504
 105220-140000

including a signal set in said filter unit from said setting unit; and

characteristic display means for displaying the characteristic calculated by said characteristic

5 calculating means.

(8.) A digital line tester comprising: 375/220 ?

a wander generator unit for generating a test signal having wander; and

10 5 a wander measuring unit for evaluating a signal passing through a digital line under testing from said wander generator unit,

characterized in that:

6 said wander generator unit includes the wander generator according to any of claims 1 through 7; and
15 said tester is configured to output a test signal synchronized with a clock signal output from said wander generator.

20 (9.) A wander generator for generating a clock signal having wander which satisfies a desired time deviation characteristic, characterized by comprising:

center frequency information setting means for setting data for determining a center frequency of the clock signal;

25 characteristic information setting means for setting characteristic information of the desired time deviation characteristic;

a fluctuating signal sequence generator unit for

105220-TH05860

372 15

generating a fluctuating signal sequence having a power spectrum density distribution characteristic of frequency fluctuations corresponding to the desired time deviation characteristic based on characteristic information set by said characteristic information setting means;

an adder for adding data set by said center
frequency information setting means to the fluctuating
signal sequence output from said fluctuating signal
sequence generator unit;

a direct digital synthesizer for outputting a frequency signal corresponding to an output of said adder; and

a clock signal output circuit for waveform shaping an output signal of said direct digital synthesizer to output a clock signal.

10. A wander generator according to claim 9,
characterized in that said fluctuating signal sequence
generator unit comprises:

noise generating means for generating a white noise signal based on a pseudo random signal;

impulse response processing means for calculating an impulse response of a transfer function for approximating a power spectrum of a white noise signal output from said noise generating means to a power spectrum density distribution characteristic of the frequency fluctuations based on the characteristic

information set by said characteristic information setting means; and

convolution processing means for convoluting the result of the calculation by said impulse response processing means with the missourians white noise signal output from the noise generating means to generate a fluctuating signal sequence having the power spectrum density distribution characteristic of the frequency fluctuations.

10 11. A wander generator according to the claim 10, characterized in that said impulse response processing means corrects an impulse response with a correction function corresponding to an error between the power spectrum density distribution characteristic of the frequency fluctuations and the transfer function.

15 12. A wander generator according to claim 10, characterized in that said convolution processing means preferentially performs the product sum calculation for smaller absolute values of the result of the calculation for the impulse response.

20 13. A wander generator according to claim 10, characterized in that said impulse response processing means is configured to perform the calculation for the impulse response each time a white noise signal is output from the noise generating means; and

25 said convolution processing means performs the convolution processing using the result of the

14. A wander generator according to claim 9,
characterized in that said fluctuating signal sequence
generator unit comprises:

data distributing means for distributing noise signals output from said noise generating means into signal paths respectively in accordance with a plurality of bands into which a frequency range of a power spectrum density distribution characteristic of the frequency fluctuations is divided to output at rates corresponding to the respective bands;

combining means for combining the noise signals at the respective rates weighted by said weighting means to generate a fluctuating signal sequence having the power spectrum density distribution characteristic of the frequency fluctuations.

15. A wander generator according to claim 10 or 14,
characterized in that said noise generating means has a

5

375/227

10

15

15

20

25

a display device; and

display control means for displaying the result of measurements of said error measuring unit and the time deviation characteristic measured by said time

deviation measuring unit on said display unit in such a manner that it can be compared with the defined time deviation characteristic.

17. A digital line tester according to claim 16,
 5 characterized in that said wander generator is the wander generator according to any of claims 9 through 15.

?
 677x clw 9
 = 10 mm Sp

18. A digital line tester comprising:

375/227

10 white noise generating means for generating a digital white noise signal;

15 a filter unit having a digital signal for storing a digital signal in a plurality of internal storage elements while sequentially shifting therein and performing product sum calculations for the contents stored in said plurality of storage element for converting a noise signal output from said white noise generating means to a noise signal of a frequency characteristic corresponding to a previously set characteristic coefficient to output the noise signal;

20 characteristic coefficient setting means (130) for setting arbitrary characteristic coefficient in said filter unit;

a multiplier for multiplying a noise signal output from said filter unit by an amplitude coefficient;

25 amplitude setting means for setting an arbitrary coefficient to the multiplier;

a frequency synthesizer for outputting a clock

00000441-072501
 105220-1406860

signal which is phase modulated by a noise signal output from said multiplier; and

initial setting means for initially setting a noise signal sequence equivalent to the contents stored in the respective storage elements of said digital filter in a state in which a noise signal of a frequency characteristic corresponding to the characteristic coefficient is being output from said filter unit in the respective storage elements of said digital filter at least in an initial phase of operation of said apparatus.

19. A digital line tester comprising:

375/227

white noise generating means for generating a digital white noise signal;

31

a filter unit having a digital signal for storing a digital signal in a plurality of internal storage elements while sequentially shifting thereinto and performing product sum calculations for the contents stored in said plurality of storage element for converting a noise signal output from said white noise generating means to a noise signal of a frequency characteristic corresponding to a previously set characteristic coefficient to output the noise signal;

characteristic coefficient setting means for setting arbitrary characteristic coefficient in the filter unit;

a multiplier for multiplying a noise signal output

FOUO 11/10/68

means;

first phase noise characteristic measuring means
for measuring a phase noise characteristic of the test
signal generated by said test signal generating means;

5 an output terminal for outputting the test signal
generated by said test signal generating means to an
external device under analysis;

an input terminal for inputting a signal output
from the device under analysis which has received the
10 test signal;

second phase noise characteristic measuring means
for measuring a phase noise characteristic of a signal
input from said input terminal in parallel with the
measurement of the phase noise characteristic for the
15 test signal by said first phase noise characteristic
measuring means;

approximation error calculating means for
calculating a difference between the phase noise
characteristic specified by said characteristic
20 specifying means and the phase noise characteristic
measured by said first phase noise characteristic
measuring means as an approximation error; and

virtual characteristic calculating means for
correcting the phase noise characteristic measured by
25 said second phase noise characteristic measuring means
with the approximation error calculated by said
approximation error calculating means to calculate a

09880441 072504
105220 "TH06560

5

10

375/285

40

15

20

25

an output terminal for outputting the test signal generated by said test signal generating means to an

